

GPS Tracker Quick Operate Guide

Step 1 Install SIM Card

- A. Make sure Sim with metal face top, clipped icon to the right as below. Or follow the Sim direction sticker on the device to operate
B. For Portable Trackers, insert Sim and you will see GREEN light flashes once and then turns to on for 30 seconds and then turns off.



(for installation Model without a indicating light, ignore Point B)



- C. Call Device's Sim number and make sure it gets through without answer.

Step 2 Set APN (Access Point Name)

This setting is to enable tracker to upload data to the server through GPRS

- A. Different Telecom provider has different APN. Please confirm APN setting on your SIM provider's website.

e.g. Vodafone APN: live.vodafone.com

e.g. Orange France APN: orange.fr

Username: orange Password: orange

(Some time APN will include username and password)

- B. Use your cellphone to send SMS *apn*AXXX*BXXX*CXXX* to the SIM number in the device. XXXX refer to APN, BXXX refers to username, CXXX refers to password. If there is no username and password required, just leave BXXXXX*CXXXXX* as blank.
(So if I am using a orange sim in France, apn setting command I should send is *apn*orange.fr*orange*orange*)

- C. Your cellphone will receive confirmation says the appointed APN is set (See screenshot as below).

Notes:

Not matter what APN settings you send to the device, system will reply confirmation as what you set. But it doesn't mean the device has connected to server successfully. You have to finish the third step to make sure the APN settings is correct.

*apn*uninet*

Apn is set to uninet.

Username: null. Password: null.

Step 3 Set Master Number

- A. Use cellphone to send SMS *master*123456*+country code and your cellphone number* to the device Sim number

- B. Your cellphone will receive confirmation says mater phone number is successfully set. And you cellphone number will be the only master phone to the tracker (See screenshot as below).

Notes:

1. 123456 is the default password, it can be changed by SMS command after the registration.

2. "+" symbol is necessary before the country code so that server is able to tell where the data is coming from.
e.g. +1 for US, +44 for UK, +39 for Italy. Please make sure the "+" symbol is under English format if you use an other local language on the phone.

3. If there is no confirmation received, It usually means APN settings is not correct, so that tracker is not able to connect the server. Please contact the Sim provider to confirm APN settings again.

*master*123456*
+8615382706688*

Notice: Cell Phone

+8615382706688 is set to master controller, the password is 123456

Step 4 Enable the data upload function

- A. Use cellphone to send SMS *routetrack*1* for 1 hour data upload, 6 locations per minute. (For other function you need to test, please see details in the user manual.)

- B. Your cellphone will receive confirmation says routetrack function will be enable for one hour.(See screenshot as below).

*routetrack*1*

Notice: System has entered routetrack function for 1 hours.

Step 5 See tracking information on-line

- A. Visit <http://www.miltown.com/>

- B. Login with master number (with +country code) and default password 123456. (See screenshot as below)

- C. Scan QR code to download Android/ IOS App.



Username : 00001302729038

Password :

Language : English

Logins



Download Android



Download Apple

D. All trackers under the same master phone number will be shown under the device list.



Icon Definition

- Offline: Device has connected to server within the past 24 hours.
- No Data: Device has activated, but there is no any server connection so far.
- Online: Device has connected to server within the past 15 minutes.
- Long Time Offline: Device has not connected to server over 24 hours.
- Not Registered: Device is not activated.
- GPS Signal
- WiFi Signal
- Cell Tower Signal
- Power Level

E. Click Device Control Panel -- History -- Select the date and time you need you view, and click Play to view the tracking history of the appointed time.



F. Click report, chose the device, date and time you need you view, and click submit and you will see the detail tracking report

Map Settings Reports Device Number : 11 ID : 00001302729038

Device Detail Report Period Report Alarm All Alerts

Detail Report

Source: 00001302729038

Display Name: 0000051507290038

Start Time Query: 2015-07-30 00:00:00

End Time Query: 2015-07-30 08:16:30

Format: HTML

Submit

For using other functions of the device. Please see user manual for details.